50W RF LED Driver(Constant current)


09.009CC.04006





Important: Read All Instructions Prior to Installation

Function introduction



Product Data


Output	Selectable Current	250mA	300mA	350mA	400mA	450mA	500mA	600mA	700mA	
	DC Voltage Range	15-48V	15-48V	15-48V	15-48V	15-48V	15-48V	15-48V	15-48V	
	Selectable Current	800mA	900mA	1000mA	1100mA	1200mA	1300mA	1400mA	1500mA	
	DC Voltage Range	15-48V	15-48V	15-48V	15-46V	15-41V	15-38V	15-35V	15-33V	
	Rated Power	50W								
	Voltage Range	200-240V AC								
	Frequency	50/60Hz								
Input	Power Factor (Typ.)	>0.9								
	Efficiency (Typ.)	87% @ 230VAC								
	Input Current	0.27A @ 230VAC								
Protection	Short Circuit	Yes								
	Over Voltage	Yes								
	Over Load	Yes								
Environment	Working Temp.	-20℃ ~ +45℃								
	Max. Case Temp.	85°C								
	Working Humidity	10% ~ 95% RH non-condensing								
	Storage Temp. & Humidity	-40°C ~ +80°C, 10% ~ 95% RH								

Safety EMC		In compliance with EN 55015, EN 61000-3-2, EN 61000-3-3, EN 61347-1, EN 61347-2-13, EN 62384, EN 61547
Other	MTBF	193.6K hrs min.@ 230VAC at full load and 25℃ ambient temperature
	Dimension	210*50*32mm (L*W*H)

Dips to set the operation current

7	ı	2	3	4	5	6	7	8	ŏ

	1 2 3 4 5 6 7 8	
50mA	$\circ \bullet \circ \circ \bullet \bullet \bullet \bullet$	80
00mA	\bigcirc	90
50mA	$\bigcirc \bullet \bigcirc \bigcirc \bullet \bullet \bigcirc \bullet$	100
O0mA	$0 \bullet 0 0 \bullet \bullet 0 0$	1100
50mA	$0 \bullet 0 0 \bullet 0 \bullet \bullet$	120
00mA	$0 \bullet 0 0 \bullet 0 \bullet 0$	130
O0mA	$0 \bullet 0 0 \bullet 0 0 \bullet$	140
00mA	0000000	150




- Dimmable LED driver with RF control
- Max. output power 50W
- 1 channel 250-1500mA constant current output
- Dips to set the operation current
- \bullet Class ${\rm I\hspace{-.1em}I}$ power supply, full isolated plastic case
- High power factor and efficiency
- To switch and dim single color LED lighting
- Compatible with a variety of single color RF remotes
- IP20 rating
- Suitable for indoor LED lighting applications
- Radio Frequency: 868/869.5/916.5/434mhz
- 3 years warranty

Safety & Warnings

- DO NOT install with power applied to device.
- DO NOT set the operation current with power applied
- DO NOT expose the device to moisture.

Wiring Diagram



Operation

Do wiring according to connection diagram.

Pair RF Receiver with RF remote:

- 1. Connect and wire up the RF receiver correctly, power on.
- 2. Turn on the remote, click the "Learning Key" button on receiver, immediately click a zone number to pair the receiver to the specified zone if the remote is a multi-zone controller (if it is a single zone remote, this step is unnecessary), then touch the color wheel or slider bar on the remote (if the remote does not have color wheel or slider bar, click or touch any keys), the connected led light on receiver flickers twice, which means well paired.

 Note: one receiver can be paired with max 8 remote controls.

PUSH DIM:


When connected to Push Switch, click push switch for switch ON/OFF, hold push switch to dim up/down the brightness

Delete the pairing:


- 1. Wire up the RF receiver correctly, power on.
- 2. Hold down the "Learning Key" button on receiver for over 3 seconds until the connected led light on receiver flickers twice, which means well deleted.

If you use multiple receivers, you have two choices:

Option 1: have all the receivers in the same zone, like zone 1



Option 2: have each receiver in a different zone, like zone 1, 2, 3 or 4



RF remote

