


Synergy 21 LED HID Corn Retrofit E40 180° 60W nw



kwh/1000h:	60,00
Lumens:	9000
Watt:	60,0
Nominal Service Life:	35000 Std.
Switching Cycles:	50000
Opt. Ambient Temperature.:	25 °C



E40 threaded base (E27 available on request)
Replacement for 250W HPS / MHL

LED: 294*SMD2835
Colour: neutral white, other light colours are available on request.
Kelvin: 4000K
CRI: >80
Beam angle: 180° and base rotatable by 350°
Wattage (W): 60
Lumen (Lm): 9000
Cover: milky
Dimmable: no
Voltage (V): 100-277VAC, 50/60Hz
Diameter: 92 mm
Total length: 275 mm
Protection class: IP64
Operating temperature: -40°~+60°C


Energy efficiency class: A+
kWh/1000h: 60

Attributes

Attribute	Value
Abstrahlwinkel:	180
CRI:	>80
Dimmbar:	nein
Lichtfarbe:	neutralweiss
Lichtfarbe in Kelvin:	4500
Lumen:	9000
Schutzklasse:	IP64
Sockel:	E40
Weight:	1.02 Kg
Warranty:	60.00 Months


Additional Images

Features:



Installation:


Lamp Installation



Step 1 | Fig1
Remove old ballast or disconnect from existing lamp holder. Remove and dispose of ballast in correct manner. (North America 100-277VAC)

Step 2 | Fig2
Reconnect directly to the existing lamp holder. (North America 100-277VAC)

Step 3 | Fig3
Install new LED replacement lamp. Please make sure the old fitting is correctly earth. (North America 100-277VAC)



Accessories

Part No.	Name
117502	Synergy 21 LED adapter for LED lamps E40->E40 long